

UNITED STATES PATENT AND TRADEMARK OFFICE
DOCUMENT CLASSIFICATION BARCODE SHEET



CATEGORY:

CLEARED

ADDRESS
CONTACT IF FOUND:

525 Rec'd PCT/PTO 28 NOV 2000

FORM PTO-1390 (REV 10-2000)		U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE	ATTORNEY'S DOCKET NUMBER
TRANSMITTAL LETTER TO THE UNITED STATES DESIGNATED/ELECTED OFFICE (DO/EO/US) CONCERNING A FILING UNDER 35 U.S.C. 371			MAT-8026US
INTERNATIONAL APPLICATION NO. PCT/JP00/01925			U.S. APPLICATION NO. (if known, see 37 CFR 1.5) 09/701226
INTERNATIONAL FILING DATE 29 March 2000 (29.03.00)		PRIORITY DATE CLAIMED 31 March 1999 (31.03.99)	
TITLE OF INVENTION BRUSHLESS MOTOR			
APPLICANT(S) FOR DO/EO/US Shinji FUKUSHIMA			
Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:			
<ol style="list-style-type: none"> 1. <input checked="" type="checkbox"/> This is a FIRST submission of items concerning a filing under 35 U.S.C. 371. 2. <input type="checkbox"/> This is a SECOND or SUBSEQUENT submission of items concerning a filing under 35 U.S.C. 371. 3. <input checked="" type="checkbox"/> This is an express request to promptly begin national examination procedures (35 U.S.C. 371(f)). 4. <input type="checkbox"/> The US has been elected by the expiration of 19 months from the priority date (PCT Article 31). 5. <input checked="" type="checkbox"/> A copy of the International Application as filed (35 U.S.C. 371(c)(2)) <ol style="list-style-type: none"> a. <input checked="" type="checkbox"/> is attached hereto (required only if not communicated by the International Bureau). b. <input type="checkbox"/> has been communicated by the International Bureau. c. <input type="checkbox"/> is not required, as the application was filed in the United States Receiving Office (RO/US). 6. <input checked="" type="checkbox"/> An English language translation of the International Application as filed (35 U.S.C. 371(c)(2)). 7. <input checked="" type="checkbox"/> Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3)) <ol style="list-style-type: none"> a. <input type="checkbox"/> are attached hereto (required only if not communicated by the International Bureau). b. <input type="checkbox"/> have been communicated by the International Bureau. c. <input type="checkbox"/> have not been made; however, the time limit for making such amendments has NOT expired. d. <input checked="" type="checkbox"/> have not been made and will not be made. 8. <input type="checkbox"/> An English language translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)). 9. <input checked="" type="checkbox"/> An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)). (UNEXECUTED) 10. <input type="checkbox"/> An English language translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)). 			
Items 11 to 16 below concern documents(s) or information included:			
<ol style="list-style-type: none"> 11. <input checked="" type="checkbox"/> An Information Disclosure Statement under 37 U.S.C. 1.97 and 1.98. 12. <input type="checkbox"/> An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included. 13. <input checked="" type="checkbox"/> A FIRST preliminary amendment. <input type="checkbox"/> A SECOND or SUBSEQUENT preliminary amendment. 14. <input type="checkbox"/> A substitute specification. 15. <input type="checkbox"/> A change of power of attorney and/or address letter. <input type="checkbox"/> Other items or information: 			

525 Rec'd PCT/PTO 28 NOV 2000

U.S. APPLICATION NO. (if known, see 37 CFR 1.5) <div style="font-size: 1.5em; font-weight: bold;">09/701226</div>	INTERNATIONAL APPLICATION NO. PCT/JP00/01925	ATTORNEY DOCKET NUMBER MAT-8026US
16. <input checked="" type="checkbox"/> The following fees are submitted: BASIC NATIONAL FEE (37 CFR 1.492(a)(1) - (5)): <input type="checkbox"/> Neither international preliminary examination fee (37 CFR 1.482) nor international search fee (37 CFR 1.445(a)(2)) paid to USPTO and International Search Report not prepared by the EPO or JPO..... \$1000.00 <input checked="" type="checkbox"/> International preliminary examination fee (37 CFR 1.482) not paid to USPTO but International Search Report prepared by the EPO or JPO \$860.00 <input type="checkbox"/> International preliminary examination fee (37 CFR 1.482) not paid to USPTO but international search fee (37 CFR 1.445(a)(2)) paid to USPTO \$710.00 <input type="checkbox"/> International preliminary examination fee paid to USPTO (37 CFR 1.482) but all claims did not satisfy provisions of PCT Article 33(1)-(4) \$690.00 <input type="checkbox"/> International preliminary examination fee paid to USPTO (37 CFR 1.482) and all claims satisfied provisions of PCT Article 33(1)-(4) \$100.00 <div style="text-align: right;">ENTER APPROPRIATE BASIC FEE AMOUNT =</div>		CALCULATIONS PTO USE ONLY <div style="border: 1px solid black; padding: 5px;"> <div style="display: flex; justify-content: space-between;"> ENTER APPROPRIATE BASIC FEE AMOUNT = \$ 860.00 </div> </div>
Surcharge of \$130.00 for furnishing the oath or declaration later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 CFR 1.492(e)).		\$
CLAIMS	NUMBER FILED	EXTRA NUMBER
Total claims	5-20 =	0
Independent claims	1-3 =	0
MULTIPLE DEPENDENT CLAIM(S) (if applicable) <input type="checkbox"/>		+ \$270.00
TOTAL OF ABOVE CALCULATIONS =		\$ 860.00
<input type="checkbox"/> Applicant claims small entity status. See 37 CFR 1.27. The fees indicated above are reduced by 1/2.		\$
SUBTOTAL =		\$
Processing fee of \$130.00 for furnishing the English translation later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 Months from the earliest claimed priority date (37 CFR 1.492(f)).		\$
TOTAL NATIONAL FEE =		\$ 860.00
Fee for recording the enclosed assignment (37 CFR 1.21(h)). The assignment must be accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property		\$
TOTAL FEES ENCLOSED =		\$ 860.00
		Amount to be refunded: \$
		Charged: \$
a. <input checked="" type="checkbox"/> A check in the amount of \$860 to cover the above fees is enclosed. b. <input type="checkbox"/> Please charge my Deposit Account No. _____ in the amount of \$ _____ to cover the above fees. A duplicate copy of this sheet is enclosed. c. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any overpayment to Deposit Account No. 18-0350 . A duplicate copy of this sheet is enclosed.		
NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status.		
SEND ALL CORRESPONDENCE TO: Lawrence E. Ashery Ratner & Prestia P.O. Box 980 Valley Forge, PA 19482 (610) 407-0700		
<div style="text-align: center;"> <div style="display: flex; justify-content: center; gap: 50px;"> <div> SIGNATURE Lawrence E. Ashery NAME </div> <div> 34,515 REGISTRATION NUMBER </div> </div> <div style="text-align: center; margin-top: 10px;"> November 28, 2000 DATE </div> </div>		

09/701226

525 Rec'd PCT/PTO 28 NOV 2000

MAT-8026US

PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant: S. Fukushima	: Art Unit:
Serial No.: To Be Assigned	: Examiner:
Filed: Herewith	:
FOR: BRUSHLESS MOTOR	:
	:

PRELIMINARY AMENDMENT

Assistant Commissioner for Patents
Washington, D.C. 20231
S I R :

Prior to examination, please amend the above application as follows:

IN THE DRAWINGS:

Please delete sheet "4/4", also labeled as "Reference numerals in the drawings".

IN THE SPECIFICATION:

After the title and before the first paragraph, please insert --THIS APPLICATION IS A U.S. NATIONAL PHASE APPLICATION OF PCT INTERNATIONAL APPLICATION PCT/JP00/01925--.

IN THE CLAIMS:

Please replace claims 1 and 4 with the following amended claims:

09/701226

[illegible][illegible]

IN THE ABSTRACT:


Please replace the abstract with the new abstract which is attached as a separate sheet.

2025 RELEASE UNDER E.O. 14176

REMARKS

Claims 1 and 4 have been amended.

Respectfully Submitted,



Lawrence E. Ashery, Reg. No. 34,515
Attorney for Applicants

LEA/dlm

Enclosures: Amended Abstract

Version with markings to show changes made

Suite 301, One Westlakes, Berwyn
P.O. Box 980
Valley Forge, PA 19482-0980
(610) 407-0700

The Assistant Commissioner for Patents is
hereby authorized to charge payment to Deposit
Account No. 18-0350 of any fees associated
with this communication.

EXPRESS MAIL Mailing Label Number: EL 769592797 US

Date of Deposit: November 28, 2000

I hereby certify that this paper and fee are being deposited, under 37 C.F.R. § 1.10 and with sufficient postage, using the "Express Mail Post Office to Addressee" service of the United States Postal Service on the date indicated above and that the deposit is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.



Kathleen Libby

106020-92000

ABSTRACT

A three-phase brushless motor includes a rotor with a permanent
5 magnet having P (P is an integer not less than two) polarities and a stator facing
the rotor and having plural coils shaped in approx. triangle or trapezoid. A
space between adjacent coils is $(360/P) \times (5/3)$ degree. Three position-
detectors, which detect the position of the rotor, is placed at intervals of $(360/P)$
 $\times (2/3)$ degree in an area where no coils are placed. This structure allows the
10 coils to be optimally shaped and placed, and realizes to reduce a number of coils
as well as improve the motor characteristics.

VERSION WITH MARKINGS TO SHOW CHANGES MADE

CLAIMS:

1 1. (Amended) A brushless motor comprising:
 2 a rotor with a permanent magnet having P (P is an integer not less
 3 than two) ~~pieces of polarity~~ polarities; and
 4 a stator facing said rotor and having a plurality of coils,
 5 wherein any one of the coils has isosceles sides interlinking with a
 6 magnetic field generated by the polarities, ~~and~~ extension lines of the isosceles
 7 sides, extending ~~through~~ along centers of winding-bundles of the coil, ~~toward a~~
 8 ~~shaft center~~ crossing each other at ~~the a~~ a shaft center and ~~form~~ having an vertex
 9 angle of $360/P$ degree.

1 4. (Amended) The brushless motor as defined in Claim 3,
 2 wherein the coils adjacent to each other ~~is~~ are spaced out at intervals of $(360/P)$
 3 $\times (5/3)$ degree.

ABSTRACT:

A three-phase brushless motor includes a rotor with a permanent magnet having P (P is an integer not less than two) ~~pieces of polarity~~ polarities and a stator facing the rotor and having plural coils shaped in approx. triangle or trapezoid. A space between adjacent coils is $(360/P) \times (5/3)$ degree. Three position-detectors, which detect the position of the rotor, is placed at intervals of $(360/P) \times (2/3)$ degree in an area where no coils are placed. This structure allows the coils to be optimally shaped and placed, and realizes to reduce a number of coils as well as improve the motor characteristics.

4 / prts

09/701226

525 Rec'd PCT/PTO 28 NOV 2000

1

P22762-P0

DESCRIPTION

Brushless Motor

5

Technical Field

The present invention relates to a three-phase brushless motor, and more particularly it relates to a placement of stator coils of the motor.

10 Background Art

A brushless motor (hereinafter referred to as a motor) has been required to have greater motor-constant "Kt" representing the torque generated per unit-electric-current in order to output greater power. For getting the greater motor-constant "Kt", in general, winding-coils are disposed occupying an area equal to or more than an area occupied by permanent magnets (hereinafter referred to as a magnet) in a disc-shaped rotor. Then a number of coils "S" increases or a number of turns of each coil increases. In this case, however; if a stator is formed by disposing flat-coreless-coils on a printed circuit board, the motor becomes expensive and incurs low productivity because the cost of manufacturing equipment rises and a number of processes increase.

When motors are downsized, the area to be occupied by a bundle of winding of the coil naturally decreases. Thus the number of turns of the coil cannot be increased. As a result, the motor constant cannot be greater. This problem provides users with the following alternative: One is just to persuade oneself that the downsizing of the motor entails the smaller motor constant, the other is to change windings and magnets to ones of higher performance and more expensive so that the influence, due to downsizing the motor, decreasing

the motor constant can be minimized.

Fig. 2A through Fig. 2C show a conventional facing and flat three-phases brushless motor. Meanwhile, the facing and flat type is referred to as a motor structure where a rotor faces a stator via a spacing in the axial direction.

5 In Fig. 2B, a size of the motor is represented by diameter "OD" extending between an outer rim of a group of the coils. When diameter "OD" measures ca. 40 mm, another diameter "ID" extending between an inner rim of the group of the coils measures ca. 20 mm. In many cases, nine coils are employed by considering the balance between the radial length and circular length of the coil.

10 In this case, since the number of polarities "P" of the disc-shaped rotor shown in Fig. 2C is 12, the fan-shaped polarity forms an angle of 30° based on $360/P$. The coils are arranged as shown in Fig. 2B, i.e. respective coils are spaced at intervals of $360/9 = 40^\circ$. Thus the space between each coil is $4/3$ of the width of the polarity. In other words, the relation (coil placement condition)

15 between the polarity width and the space between each coil is expressed as $(360/P) \times (4/3)$, with considering a placement of the polarities. Thus in this case, 40 degree interval is calculated.

In Fig. 2B, respective coils forming U, V and W phases are placed. U phase is formed by coils U1, U2 and U3. V phase is formed by coils V1, V2 and

20 V3. W phase is formed by coils W1, W2 and W3. Nine coils in total are disposed on printed circuit board 2. Width "A" of winding-bundle of each coil is restricted by soldering land 4 and the adjacent coils. The soldering land 4 is disposed inside of each coil and used for terminating the coil-wire end.

Each coil, in particular, comprises numbers of winding-bundles, therefore,

25 0.01 mm dispersion of winding diameter causes 0.2 mm dispersion on coil's outer diameter when the winding turns 20 times. This dispersion and the work of fixing each coil onto the printed circuit board should be taken into consideration,

the space to the adjacent coils thus should be ca. 1 mm in general. Further, another space is required for disposing magnetic sensor 5 — a position detector — for detecting a rotor position. Sensors 5 are placed inside respective three coils, i.e. coils U1, V1 and W1. The width "A" of winding-bundle of these three coils thus become narrower than those of other 6 coils. This restriction reduces a number of turns of these three coils, and prevents the motor constant from becoming greater. The size of the magnetic sensor and the area of the soldering land are difficult to be reduced in proportion to downsizing the motor, therefore, the influence of this restriction adversely increases more than proportional at greater downsizing of the motor.

When an isosceles angle of the coil matches up to 30 degree which the rotor polarity forms, windings of the coil outwardly bulge out by ca. 1.7 mm on each side, and inwardly bulge out by ca. 0.9 mm on each side. When the space between the adjacent coil is considered, there is little space for disposing the winding outside the isosceles angle 30 degree. Therefore, if the number of turns of the coil should be increased, almost of all the windings should be disposed inside the angle 30 degree. As a result, the isosceles angle becomes practically less than 30 degree.

As such, in the case that the isosceles angle becomes smaller, one of a rotor polarity reaches the position, in a winding-bundle of one of isosceles sides, where the maximum torque is produced, then the other rotor polarity is displaced from the position, in another winding-bundle of the other side of isosceles sides, where the maximum torque would be produced. Therefore, as one entire coil, this coil cannot produce the maximum torque. As a result, the motor constant becomes smaller than the case where the isosceles angle forms 30 degree.

In the case that much more coil's windings are disposed inside of polarity

angle 30 degree, a point, where torque is produced in a direction reverse to normal rotating direction of the motor, is provided, so that the motor constant incurs some loss. This reversal point also causes vibration of the motor.

Fig. 2A illustrates this situation. Fig. 2A shows a relation between cross section of winding-bundle of the coil and a position of the rotor shown in Fig. 2B. Coil's winding-bundles 8 and 9 are disposed with respect to polarity 7 disposed every 30 degree in rotor 6. Winding-bundles 8 and 9 form the same windings, and e.g. when electric current runs from this side to that side in bundle 8, the current runs from that side to this side in bundle 9. In other words, when different polarities face bundles 8 and 9 respectively, torque is produced in the same direction respectively; however, when the same polarities face bundles 8 and 9, torque is generated in the reverse direction and cancels each other. As shown in Fig. 2A and Fig. 2B, numbers of windings are disposed inside the 30 degree, and in this case, when rotor 6 revolves and polarity 7 reaches the position shown in Fig. 2A, Z-section of bundle 9 faces the same polarity of bundle 8. Thus reverse torque is produced in the same bundle 9.

The following prior art has been known for addressing the problem discussed above: Sensors 5 are collected and placed in the area where the coils are not disposed, as shown in Fig. 3. The coils are placed at conventional intervals of $(360/P) \times (4/3)$. For instance, 10 polarities with 6 coils can improve the problematic situation. In Fig. 3, based on the conventional coil placement condition discussed above, respective coils forming U, V and W phases are placed at intervals of 48 degree because of $P = 10$. In other words, U phase coils are formed by coils U1 and U2, V phase coils are formed by coils V1 and V2, and W phase coils are formed by coils W1 and W2. In total 6 coils are disposed on the printed circuit board.

These 6 coils are massed in five areas disposed in every 48 degree, i.e.

total area covered by $48 \times 5 = 240$ degree, so that the space for accommodating sensors 5 can be obtained. Sensors 5 can be placed at intervals of $(360/P) \times (4/3)$ degree or $(360/P) \times (2/3)$ degree. The example shown in Fig. 3 shows the interval of $(360/P) \times (2/3)$ degree i.e. 24 degree.

5 However, when diameter "OD", extending the outer rim formed by each coil, is small, soldering lands 3 outside the respective coil-wire ends become closer to sensor 5. Thus when the end of each coil-wire is soldered, the coil-wire end tends to short with the terminal of sensor 5. The coil-wire end is, in particular, easy to be deformed so that it is difficult to regulate its position
10 during the work, and the disperse of length of coil-wire end is large due to terminating work, thus the coil-wire ends need, in general, a rather longer length preliminarily. Soldering lands 3 are placed on printed circuit board 2; however, the manufacturing technique allows rather great disperse on positional accuracy of lands 3, so that ca. 0.2 mm relative displacement with
15 sensor 5 should be allowed. Due to the reasons discussed above, enough space between land 3 and sensor 5 is needed. Therefore, when diameter "OD" is small, sensors 5 cannot be massed outside the coils, and they should be placed inside the coils instead.

In the case of the conventional motor discussed above and whose diameter
20 "OD" is not more than 40 mm, spaces for respective coils should be small. Further, the number of turns of the coils are difficult to increase because the space for the soldering lands and the magnetic sensors should be reserved as well as good workability should be prepared. As a result, the motor constant cannot be greater. On the contrary, the motor constant decreases more than
25 proportional at greater downsizing of the motor when the area ratio is considered between coils' occupying area vs. the area occupied by the magnetic sensors besides considering the dimensionally restricted soldering lands.

Other problems have been already discussed: i.e. the isosceles angle of the coil is practically smaller than the fan-shaped isosceles angle that forms the rotor polarity, so that the torque generated incurs some loss, and reverse torque is produced to counteract the torque and cause vibration of the motor.

5

Disclosure of the Invention

The present invention addresses the problems discussed above, and a brushless motor of the present invention comprises the following elements:

a rotor with a permanent magnet having "P" (P is an integer equal to two or more than two) pieces of polarity; and

a stator facing the rotor and having a plurality of coils.

The coil has isosceles sides which interlink with the magnetic field produced by the polarities, and extension lines of the isosceles sides—extending through centers of winding-bundles of the coil—toward a shaft center cross each other at the shaft center and form an angle of $360/P$ degree.

This structure restrains the lowering of a motor constant due to downsizing the motor. Further, an optimum shape and optimum placement of the coils allow a number of coils to be reduced from the same size of the motor.

Brief Description of the Drawings

Fig. 1A is a cross section illustrating the relation between rotor's position and winding-bundles of a brushless motor in accordance with an exemplary embodiment of the present invention.

Fig. 1B shows a stator of the brushless motor in accordance with the exemplary embodiment of the present invention.

Fig. 1C shows a rotor of the brushless motor in accordance with the exemplary embodiment of the present invention.

Fig. 2A is a cross section illustrating the relation between rotor's position and winding bundles of a conventional brushless motor (12 polarities and 9 coils).

Fig. 2B shows a stator of the conventional brushless motor.

5 Fig. 2C shows a rotor of the conventional brushless motor.

Fig. 3 shows a stator of another conventional brushless motor (10 polarities and 6 coils).

Detailed Description of the Preferred Embodiment

10 An exemplary embodiment of the present invention is demonstrated hereinafter with reference to the accompanying drawings.

The exemplary embodiment is demonstrated with reference to Figs. 1A, 1B and 1C.

15 Fig. 1A is a cross section illustrating the relation between rotor's position and winding-bundles of a brushless motor in accordance with the exemplary embodiment of the present invention. Fig. 1B shows a stator of the same brushless motor, and Fig. 1C shows a rotor of the same brushless motor.

Fig. 1A through Fig. 1C illustrate that the present invention reduces 9 coils conventionally required to 6 coils which are employed in a three-phase
20 brushless motor having 12 rotor-polarities (P) and the diameter measures ca. 40 mm. Each coil is formed by flat coreless windings and preferably shaped in roughly a triangle or a trapezoid. The rotor is shaped in a disc.

As shown in Fig. 1B, respective coils forming U-phase, V-phase and W-phase are placed at intervals of $(360/P) \times (5/3)$ degree. Since $P = 12$, the
25 interval is calculated to be 50 degree. In other words, U-phase is formed by coils U1 and U2, V-phase is formed by coils V1 and V2, and W-phase is formed by coils W1 and W2. As such, three phases of the stator are formed by two coils

of respective phases. The above formula thus results in 50 degree interval.

As shown in Fig. 1B, the coil winding-bundle forming isosceles sides of coil V1 is placed with respect to the one of angle sides forming $360/P$ degree so that one of the isosceles sides and the other side are placed within $360/(4 \times P)$ degree both inside and outside of the angle side. In the case of $P = 12$, angle sides—extending through the center of two winding-bundles of a coil—form 30 degree. Each winding-bundle is placed within 7.5 degree inside and outside the angle side as a center.

Thus, for instance, in the case of the motor having diameter OD of ca. 40 mm, diameter ID is, in general, ca. 20 mm due to structural restriction by bearings and the like. In this case, when the isosceles sides of each coil form 30 degree, the windings piled up from the bundle center measures 3.5 mm width on both sides at the outer rim ($\phi 40$) and 1.7 mm width on both sides at the inner rim ($\phi 20$). This structure allows the windings to be placed outside the angle of 30 degree with enough space even if the clearance between the adjacent coil is reserved.

When six coils are arranged at intervals of 50 degree, the area where no coils are placed extends over 60 degree (in this embodiment, the area extends 65 degree.) In this area, three magnetic sensors HU, HV, HW, which are position detectors of the rotor, are placed at intervals of $(360/P) \times (2/3)$ i.e. 20 degree. This structure allows the place for respective coils to be larger than the case where the magnetic sensors are placed within the coils.

Relations of physical placement between the three phase coils and three position detectors are further detailed hereinafter with reference to Fig. 1B. The stator coil comprises three phases, namely, U-phase, V-phase and W-phase. Each phase is formed by coils U1 and U2 coupled in series, V1 and V2 coupled in series, W1 and W2 coupled in series. The center of coil U1 is spaced out from

position detector HU by 60 degree. In the same manner, the center of coil V1 is away from position detector HV by 90 degree, and the center of coil W1 is away from detector HW by 180 degree. Respective detectors are arranged at intervals of 20 degree.

5 The structure of the three-phase motor in accordance with the embodiment practically makes the three-phase motor operative as same as the conventional brushless motor. This is demonstrated hereinafter.

10 In the conventional motor, with respect to a signal detected in a U-phase coil, a signal detected in a V-phase coil is shifted by 240 degree in electrical angle. With respect to the signal detected in the V-phase coil, a signal detected in a W-phase coil is shifted by also 240 degree in electrical angle. Thus the signal in the W-phase coil is shifted from the signal in the U-phase coil by 480 electrical angle; however a shift by 360 electrical angle is identical to the same phase, thus the signal in the W-phase coil is eventually shifted from that in the
15 U-phase coil by 120 electrical angle. The detected signals in the three phases are shifted by 120 electrical angle respectively. This is the condition for the three-phase brushless motor to function.

20 On the other hand, in the brushless motor of the present invention, with respect to a signal detected in coil U1, a signal detected in coil V1 is shifted by 300 degree in electrical angle. With respect to the signal detected in coil V1, a signal detected in coil W1 is shifted by 300 electrical angle. As a result, the signal detected in coil W1 is shifted from that in coil U1 by 600 electrical angle. Since the shift of 360 electrical angle turns out the same phase, the signal in coil W1 is eventually shifted from the signal in coil U1 by 240 electrical angle. If
25 coil W1 is shifted from coil U1 by 480 degree as same as the conventional motor, the three-phase brushless motor of the present invention satisfies the condition for functioning as the motor; however, the shift value is 300 degree. This does

not allow this motor to function as the motor. Then the winding of coil V1 is wound in the opposite direction to that of coil U1, thereby shifting coil V1 from coil U1 by 180 electrical angle. As a result, coil V1 is shifted from coil U1 by 480 degree.

5 With respect to coil U1, coil U2 is shifted by 150 degree in mechanical angle, that means the shift amount is 900 degree in electrical angle. Since 360 degree shift in electrical angle is equivalent to the same phase, coil U1 has 180 degree phase difference in electrical angle from coil U2. Therefore, the winding of coil U2 is wound in the opposite direction to that of coil U1 so that coils U1
10 and U2 can be in the same phase in electrical angle.

In the same manner, coils V1 and V2, coils W1 and W2 are shifted by 150 degree in mechanical angle respectively. Thus the winding of one of the coils is wound in the opposite direction to that of the other, so that both the coils in respective cases are in the same phase in electrical angle. In other words,
15 three windings of coils U2, V1 and W2 are wound in the opposite directions to those of coils U1, V2 and W1, so that the signals of respective coils of three phases are shifted by 120 electrical angle from each other. As a result, this motor can function as a three-phase brushless motor.

The effect discussed above can be realized also by changing a coupling
20 direction between respective coils through wiring the printed circuit board, instead of changing the winding direction of the coil.

As discussed above, the structure of the brushless motor of the present invention allows the coils to be disposed at optimal places and shaped in an optimal form, so that loss of a motor constant is restrained. In the attempt at
25 downsizing a motor, the loss of the motor constant due to restriction of placing coils can be reduced, thereby increasing the motor constant. Further, a number of coils can be reduced, thanks to the optimal placement and optimal shape of

the coils, from the conventional motor of the same size.

Industrial Applicability

The present invention relates to coil placement in a stator applicable to a
5 brushless motor. To be more specific, it relates to a three-phase brushless
motor comprising a rotor with a permanent magnet having P pieces of polarity
and a stator facing the rotor and coming with a plurality of coils forming approx.
triangles or trapezoids. In this three-phase brushless motor, space between
adjacent coils measures $(360/P) \times (5/3)$ degree, and three position detectors
10 for detecting the position of the rotor are placed at intervals of $(360/P) \times (2/3)$
degree. The detectors are placed in the area where no coils are disposed. This
structure allows the coils to be optimally placed and shaped in optimal form, and
also realizes to reduce a number of coils as well as increase a motor constant.

CLAIMS

1. A brushless motor comprising:

5 a rotor with a permanent magnet having P (P is an integer not less than two) pieces of polarity; and

a stator facing said rotor and having a plurality of coils,

10 wherein any one of the coils has isosceles sides interlinking with magnetic field generated by the polarities, and extension lines of the isosceles sides, extending through centers of winding-bundles of the coil, toward a shaft center cross each other at the shaft center and form an angle of $360/P$ degree.

2. The brushless motor as defined in Claim 1, wherein an outer rim of the coil measures not more than $\phi 40$ mm.

15 3. The brushless motor as defined in Claim 1, wherein the coil winding-bundles forming the isosceles sides are disposed within an area covered by an angle of $360/(4 \times P)$ degree both inside and outside with respect to a center of the angle of $360/P$ degree.

20 4. The brushless motor as defined in Claim 3, wherein the coils adjacent to each other is spaced out at intervals of $(360/P) \times (5/3)$ degree.

25 5. The brushless motor as defined in Claim 4 further comprising three position detectors for detecting a position of said rotor, wherein said detectors are placed at intervals of $(360/P) \times (2/3)$ degree and in an area where the coils are not placed.

ABSTRACT

A three-phase brushless motor includes a rotor with a permanent magnet having P (P is an integer not less than two) pieces of polarity and a stator facing the rotor and having plural coils shaped in approx. triangle or trapezoid. A space between adjacent coils is $(360/P) \times (5/3)$ degree. Three position-detectors, which detect the position of the rotor, is placed at intervals of $(360/P) \times (2/3)$ degree in an area where no coils are placed. This structure allows the coils to be optimally shaped and placed, and realizes to reduce a number of coils as well as improve the motor characteristics.

FIG. 1A




FIG. 1B




FIG. 1C




FIG. 2A




FIG. 2B




FIG. 2C





FIG. 3



Reference numerals in the drawings

- 2 Printed circuit board
- 3 Soldering land for a coil end (outside a coil winding)
- 4 Soldering land for a coil end (inside a coil winding)
- 6 Disc-shaped rotor
- 7 Polarity
- 8, 9 Cross section of a coil
- 10 Center line of winding-bundle of a coil
- A Width of a winding-bundle of a coil
- HU, HV, HW position detector (magnetic sensor)
- U1, U2, V1, V2, W1, W2 coil
- Z A section where reversal torque is produced

Declaration and Power of Attorney For Patent Application

English Language Declaration

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name,

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled

BRUSHLESS MOTOR,

the specification of which is attached hereto unless the following box is checked:



was filed on March 29, 2000 as

United States Application Number or PCT International Application Number PCT/JP00/01925

and was amended on November 28, 2000 (if applicable).

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR § 1.56.

I hereby claim foreign priority benefits under 35 U.S.C. §119(a)-(d) or § 365(b) of any foreign application(s) for patent or inventor's certificate, or § 365(a) of any PCT International application which designated at least one country other than the United States, listed below and have also identified below by checking the box, any foreign application for patent or inventor's certificate, or PCT International application having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)

Priority Not Claimed

11-092585

Japan

31 March 1999

(Number)

(Country)

(Day/Month/Year Filed)

☐

(Number)

(Country)

(Day/Month/Year Filed)

☐

I hereby claim the benefit under 35 U.S.C. § 119(e) of any United States provisional application(s) listed below.

(Application Number)

(Filing Date)

(Application Number)

(Filing Date)

I hereby claim the benefit under 35 U.S.C. § 120 of any United States application(s), or 365(c) of any PCT International application designating the United States, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of 35 U.S.C. § 112, I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application:

(Application Number)

(Filing Date)

(Status - patented, pending, abandoned)

(Application Number)

(Filing Date)

(Status - patented, pending, abandoned)

POWER OF ATTORNEY: As a named inventor, I hereby appoint the following attorney(s) and/or agent(s) to prosecute this application and transact all business in the Patent and Trademark Office connected therewith:

Paul F. Prestia	Reg. No. <u>23,031</u>	Lawrence E. Ashery	Reg. No. <u>34,515</u>	Jack J. Jankovitz	Reg. No. <u>42,690</u>
Allan Rather	Reg. No. <u>19,717</u>	Christopher R. Lewis	Reg. No. <u>36,204</u>	Jonathan H. Spadt	Reg. No. <u>45,122</u>
Andrew L. Ney	Reg. No. <u>20,300</u>	Robert L. Andersen	Reg. No. <u>25,771</u>	Christopher I. Halliday	Reg. No. <u>42,621</u>
Kenneth N. Nigon	Reg. No. <u>31,549</u>	Joshua L. Cohen	Reg. No. <u>38,040</u>	Scott A. Mckeown	Reg. No. <u>42,866</u>
Kevin R. Casey	Reg. No. <u>32,117</u>	Daniel N. Calder	Reg. No. <u>27,424</u>		
Benjamin E. Leace	Reg. No. <u>33,412</u>	Louis W. Beardell, Jr.	Reg. No. <u>40,506</u>		
James C. Simmons	Reg. No. <u>24,842</u>	Jacques L. Etkowicz	Reg. No. <u>41,738</u>		

Address all correspondence to: Lawrence E. Ashery

Ratner & Prestia, Suite 301, One Westlakes, Berwyn, P.O. Box 980, Valley Forge, PA 19482-0980

Address all telephone calls to: Lawrence E. Ashery at (610) 407-0700.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full name of sole or first inventor (given name, family name) Shinji Fukushima

Inventor's signature Shinji Fukushima

Date January 26, 2001

Residence Ehime, Japan

Citizenship Japanese

Post Office Address 1620-46, Hagyu, Niihama-shi,

Ehime 792-0050 Japan

Full name of second joint inventor, if any (given name, family name) _____

Second Inventor's signature _____

Date _____

Residence _____

Citizenship _____

Post Office Address _____



Additional inventors are being named on separately numbered sheets attached hereto.